

## HE101-U HDMI 2.0 4K/60 4:4:4, HDCP 2.2 Signal Equalizer





The **HE101-U** Signal Equalizer provides a convenient installation solution for extending and amplifying high-bandwidth HDMI 2.0 signals using standard HDMI cables in a home or office environment.


## Key Features

- Supports cable lengths up to 33 ft. (10 m) at 4K/60 (4:4:4) resolutions, up to 66 ft. (20 m) at 4K/60 (4:2:0) resolutions, and up to 132 ft. (40 m) at resolutions up to 1080p
- High bandwith support up to 18 Gbps
- HDCP 2.2 compliance
- Proprietary signal re-generation & repeating technology enables maximum transmission distance
- Draws power directly from the HDMI source(Micro-USB power injection optional)
- Seamless, easy integration

## Technical Specification

INPUT TYPE	HDMI Single Link , 1 port
OUTPUT TYPE	HDMI Single Link , 1 port
SUPPORTED INPUT/	Ultra HD/4K
OUTPUT RESOLUTION	Up to 4096 x 2160 @ 50/60Hz
	(RGB 4:4:4 YCbCr 4:4:4, 4:2:2, 4:2:0)
CONNECTOR TYPE	HDMI 19 Pin Female
	Micro USB power jack
SUPPORTED FORMAT	HDMI 2.0
HDCP COMPLIANT	Yes, Pass thru, HDCP 2.2
MULTI-CHANNEL AUDIO	Yes, Pass thru
HDR SUPPORT	Yes, Pass thru
CEC SUPPORT	Yes, Pass thru
EDID	Pass thru
POWER	HDMI (via HDMI pin# 18) or
	Micro USB DC +5V , 2A, Max 10W
	* Micro USB is an optional, does not
	come with the unit
DIMENSION	1.1" x 2.0" x 0.8" (28 x 52 x 21 mm)
WEIGHT	0.13 Lbs   60g

Application Diagram



PureLink purelinkav.com

All brand names, product names and trademarks are the property of their respective owners. Certain trademarks, registered trademarks, and trade names may be used to refer to either the entities claiming the marks and names or their products. PureLink disclaims any proprietary interest in the marks and names of others. PureLink is not responsible for errors in typography or photography. @2017 Dirovision LLC | PureLink